


# AC DRIVE OPTIONS

## General Options (not HP dependent)

Description	Part No.	Use With	 OS-41
OS-41 Operator Panel/Parameter Copy Unit	V071A012-DR41	All*	
OS-42 Operator Panel w/Speed Potentiometer	V071A012-DR42	HF430	
RC-2 2-Meter Remote Mounting Cable	V071A012-RC2	All	
PG-1 Encoder Feedback Board	V071A012-PG1	HF430	
DN-1 DeviceNet Interface Board	V071A012-DN1	HF430	
PB-1 Profibus Interface Board	V071A012-PB1	HF430	
PS-1 Prog. Software w/RS232 to RS485 converter	V071A012-PS1	All	

\*For remote mounting only when used with SF320 and HF320 drives.

## Dynamic Braking Options (HF320 & HF430 Only)

### HF320 – 230V (100% Braking Torque, 10% Duty Cycle)

HP	Drive Model	DBR Model	Part Number	Figure	Dimensions H x W x D (mm)
1/4	HF3202-A20-W	DBR200-200E1	V060A031	1	102 x 254 x 127
1/2	HF3202-A40-W	DBR200-200E1	V060A031	1	102 x 254 x 127
1	HF3202-A75-W	DBR80-300E1	V060A032-01	1	102 x 254 x 127
2	HF3202-1A5-W	DBR80-300E1	V060A032-01	1	102 x 254 x 127
3	HF3202-2A2-W	DBR40-600E	AEPA1469	1	102 x 508 x 127
5	HF3202-3A7-W	DBR40-600E	AEPA1469	1	102 x 508 x 127
7.5	HF3202-5A5-W	DBR20-1300E	AEPA3902-01	2	127 x 356 x 330
10	HF3202-7A5-W	DBR20-1300E	AEPA3902-01	2	127 x 356 x 330

### HF320 – 460V (100% Braking Torque, 10% Duty Cycle)

HP	Drive Model	DBR Model	Part Number	Figure	Dimensions H x W x D (mm)
1/2	HF3204-A40-W	DBR750-200E1	V060A033	1	102 x 406 x 127
1	HF3204-A75-W	DBR750-200E1	V060A033	1	102 x 406 x 127
2	HF3204-1A5-W	DBR250-400E2	V060A032-02	1	102 x 254 x 127
3	HF3204-2A2-W	DBR160-600E2	V060A032-06	1	254 x 356 x 127
5	HF3204-3A7-W	DBR160-600E2	V060A032-06	1	254 x 356 x 127
7.5	HF3204-5A5-W	DBR75-1300E	V0600004-9	2	127 x 356 x 330
10	HF3204-7A5-W	DBR75-1300E	V0600004-9	2	127 x 356 x 330

